




Palm Zire 71 Motherboard/Screen Replacement

Written By: Jinxian Jiang



INTRODUCTION

This is a guide for disassembling the motherboard and the screen.

TOOLS:

- [Phillips #00 Screwdriver](#) (1)
 - [iFixit Opening Tools](#) (1)
 - [T5 Torx Screwdriver](#) (1)
-

Step 1 — Preparation



- Flip the phone so it's facing screen-side down.
- Slide the back cover upward to open.

Step 2 — Top Screws (2) Removal



- Use a Torx T5 screwdriver to remove the top two screws.

Step 3 — Bottom Screws (3) Removal



- Remove the back sticker.
- Remove the three bottom Phillips #00 screws.

Step 4 — Front Panel Removal



- Flip the phone over so it's facing screen-side up.
- Slide the screen upward by a few millimeters without detaching the screen.
- Use the plastic opening tool to pry off the front panel.

Step 5 — Bracket and Speaker Removal



- Remove the bottom two Phillips #00 screws.
- Remove the bracket.
- Use the plastic opening tool to pry off the speaker.

Step 6 — Back Cover




- Slide the back cover off.

Step 7 — Battery




- Remove the Philips #00 screw
- Remove the sliver metal piece

Step 8




- Remove the Philips screws #00
- Remove the rear blue panel by prying both sides using the plastic opening tool

Step 9




- Remove the black plastic sticker
- Pull the tap up to remove the metal cap

Step 10



- Remove the cable by pinching the sides and pulling
- Pry off the battery with the plastic opening tool
- Insert the new battery

Step 11 — Motherboard/Screen



- Remove Philips screw #00
- Remove black plastic top part

Step 12



- Pull off the orange cable
- Now the screen and the motherboard can be separated
- Finished

To reassemble your device, follow these instructions in reverse order.

This document was generated on 2021-07-13 07:02:12 AM (MST).

